



# Video Tracking Controller

## TS-0699



### Description

\*Mixer Digital Amplifier with MP3/TUNER/Bluetooth, used for background music playback of small and medium-sized indoor venues such as small and medium-sized supermarkets, shopping malls, and leisure cafes.

### Feature

\*5 HD digital component serial interface (SD-SDI, HD-SDI and 3G-SDI) signal input.

\*2-way HD digital component serial interface (SD-SDI, HD-SDI

and 3G-SDI) signal output.

\*Video input resolution up to 1920 × 1080P@60Hz.

\*Video output resolution up to 1920 × 1080P@60Hz.

\*Dial switch select camera baud rate and communication protocol.

\*The serial port to connect the meeting host to achieve camera tracking.

\*Two-way camera 485 control port, up to 5 cameras.

\*Support Pelco\_D protocol and VISCA camera with 485 control port.

Model	TS-0699
Video Interface	BNC
Gain	0dB
Lock Rate	Automatic
Operating Standard	SMPTE259M; SMPTE292M; SMPTE424M
Signal Type	SD-SDI, HD-SDI, 3G-SDI
Maximum Resolution	1920×1080P@60Hz
Return Loss	<-15 dB @ 1MHz ~ 1.5GHz; <-10 dB @ 1.5GHz ~ 3GHz
Maximum Rate	2.97Gbps
Input and Output Levels	0.80Vp-p+/- 10%
Input and Output Impedance	75 Ω
Balanced Type	Adaptive
Maximum Input Distance	100 meter
Control Port	1×CONTROL, 1×CONFERENCE, Connect computer control or conference host to achieve camera tracking
Power	AC100-240V 50~60HZ
Maximum Power Consumption	15W
Weight	about 3Kg
Size (mm)	484×210×44mm
Color	black
Operating Temperature	-10°C~ +60°C
Environment Humidity	Relative humidity, no condensation