



Features

- * Micro-PC controlled, soft touch zone key
- * 10 music amplifier and 10 EMC/paging amplifier inputs
- * 1 amplifier for 10 zones or 10 amplifier for 10 zones speaker
- * 10 separate zone and all zone fire alarm triggering inputs
- * Alarm out for other voice message alarm equipments
- * Front panel 10 zone select key with indicator and all zone select
- * Separate zone and all zone EMC input to meets different needs
- * BGM and EMC zone working state indicator; light from green to red when there is paging and EMC
- * Memory function in case of power off.

Optional

- * With DC 24V input
- * Panel without handhold

Specifications

Model	T-6217
Input	10BGM amp inputs, 10 EMC inputs: 70V or 100V, COM
Output	10 channel speaker outputs, each channel max output 500W
Controls	Individual zone selectors Power switch
Indicators	Power LED, channel status LEDs-BGM or priority
Power Supply	~110V/60Hz or ~230V/50Hz
Power Consumption	35W
Weight	5.3Kg
Dimensions	484x303x88mm
Finish	Panel: aluminum plate, black or golden (optional) Case: steel plate, black

Connections

