



## **Features**

- \* Ambient noise sensor for ambient noise controller
- $\ensuremath{^*}$  The system support both serial connection parallel connection
- \* The system sensor capacity is 16 units
- \* Max 16 units sensor can be connected to four channels or one channel
- \* End-user self defined sampling frequency period
- $\ensuremath{^*}$  Collect the surrounding ambient level and feedback to controller
- \* Full digital sensor solution for more accurate detection
- $\ensuremath{^*}\xspace$  Cascaded connection by line in and line out
- \* High & low filter frequency adjustable
- \* Max communication distance is 3kms.
- $\ast$  Communication cable through universal speaker cable

## **Specifications**

Model	T-6251B	
Microphone Type	Condenser microphone	
<b>Communication Model</b>	Bus line	
Noise Frequency filter	4	
Output level	1V/600 Ω	
Frequency response	80-18KHz(+1/-3dB)	
THD	≪۱%	
Power consumption	4W	
Communication distance	ЗКМ	
Power supply	$\sim$ 230V/50Hz	
Dimension	205x205mm	
Weight	0.6kg	



## Connections

