



Description

Digital infrared receiver charging unit for the charging function, the red light indicates the battery and charging stand is in poor connection, if the charging indicator is in orange color, it means the unit is in charging status, if the indicator light of charging stand turns green, it represents the battery has been fully charged.

Features

- * It can simultaneously charge 25 receiver units.
- * Power input has tandem function.
- * Quick Charging time is 2.5 hours: the maximum charge time is 8 hours.
- * Charging unit is not only for charging function, but also for keeping the receivers.

Specifications

Model	TS-0670HC
Input Voltage	~100V-240V 50-60Hz
The Maximum Power Consumption	100W
Standby Power Consumption	17W
Dimension(mm)	627(L)×385(W)×238(H)
Weight	10Kg